

YBN-R/3(SCI)

Short-Circuit Isolator Base

Features

- Features integral SCI
- Easy to fit
- Slim profile
- Matches standard base colours
- Marine and SIL2 approved variants available



Description

Model YBN-R/3(SCI) is a sensor mounting base featuring an integral short-circuit isolator which will detect and isolate short-circuits on the loop. When a short-circuit is detected during power up the unit will drop the power to the rest of the loop.

The YBN-R/3(SCI) is compatible with the ESP range of sensors and does not require a loop address. A remote fire LED facility is provided when a sensor is attached to the base.

NOTE: A fitted sensor will still be powered when this device is isolating.

Specification	
Ordering codes	YBN-R/3(SCI) - Ivory, YBN-R/3(WHT)-SCI - White, YBN-R/3(BLK)-SCI - Black
Protocol	ESP
Operating voltage	17 - 41 VDC (24 VDC nominal)
Standby current	60 µA
Current drawn by isolator during fault condition	< 4 mA
Maximum current consumption from remote LED	10 mA (limited by attached sensor)
Maximum continuous current	1 A
Maximum quantity per loop	127* ¹
Ambient temperature range	-10 °C to +50 °C
Relative humidity	10% to 95% RH (at 40°C)
Colour and case material	Ivory, White or Black ABS
Fixing centres	48 mm through to 74 mm
Maximum wire thickness	2.5 mm ² /terminal
Weight (g) / Dimensions (mm)	79 / Ø 100 x H 13.7

*¹ Check with Fire alarm control panel manufacturer for maximum loop quantities

See AP0127 for short-circuit isolator specifications



For further information visit our website.
Hochiki reserves the right to alter the specification of its products from time to time without notice. Although every effort has been made to ensure the accuracy of the information contained in this document it is not warranted or represented by Hochiki to be a complete and up-to-date description. Check online for current version.

www.asafire.ir

HOCHIKI ISS4 AUG24
